

## CONNECTOR POSITION ASSURANCE DEVICE

### BACKGROUND OF THE INVENTION

[01] Certain embodiments of the present invention generally relate to a connector position assurance device (CPA) for use with electrical connector housings, and an electrical connector system having a connector position assurance device.

[02] Electrical connectors have been proposed that utilize a latch or retention assembly to maintain connector halves in a fully mated position, along with a CPA. When the connector halves are mated and the latch or retention assembly is positioned to maintain contact between the connector halves, the CPA is moved to a position that indicates the connector halves are properly connected. Thus, the CPA provides a means to assure that the connector halves are fully mated.

[03] It is advantageous to add the use of a CPA to an existing connector half that was originally designed for use without a CPA. Conventional connector assemblies utilizing CPAs, however, feature connector halves that were both designed for use with CPAs, so conventional connector halves utilizing CPAs cannot conveniently be retrofitted to mate with existing connector halves. Additionally, it is desirable to have an interchangeable connector half that may be used interchangeably with both a mating connector half in a connector assembly utilizing a CPA and a different mating connector half in a connector assembly without a CPA, wherein the interchangeable connector half is manufactured as simply and economically as possible.

[04] Also, conventional connector assemblies using CPAs and latches can suffer from other drawbacks. For example, the CPA may inadvertently advance to a position indicating the connector halves are mated when the connector halves are separated. The CPA may also not be secured in position when the connector halves are mated.

[05] A connector is needed with an improved CPA and connector half configuration that overcomes the above-noted and other disadvantages of conventional connectors.

#### BRIEF SUMMARY OF THE INVENTION

[06] At least one embodiment of the present invention is provided including an electrical connector assembly comprising a connector position assurance device (CPA), a first connector housing, a second connector housing, a retention assembly, a second retention feature, and a CPA mounting assembly. The CPA includes a retention assembly locking element and a CPA retention element. One of the first and second connector housings has a body section with a mating interface on one end, and the other connector housing has an opening to receive the mating interface. A retention assembly is mounted to the first connector housing to maintain the first and second connector housings in contact when they are mated. The retention assembly includes a first housing retention feature, a CPA retention feature, and a locking contact surface. The retention assembly is movable between locked and unlocked positions. A second housing retention feature is mounted to the second connector housing. The second housing retention feature cooperates with the first housing retention feature to maintain contact between the first and second connector housing when they are mated.

[07] The first connector housing has a CPA mounting assembly mounted thereto. The CPA is slidably mounted to the CPA mounting assembly and is movable to first and second positions. In its first position, the CPA permits biasing of the retention assembly and engagement and disengagement of the first and second connector housings. When the CPA is in the second position, the retention assembly locking element cooperates with the locking contact surface to prevent the retention assembly from moving to the unlocked position, thus preventing engagement and disengagement of the first and second connector housings. The CPA retention element cooperates with the CPA retention feature to maintain the CPA in the second position.

[08] Additionally, the CPA may include a first CPA beam and at least one second CPA beam, and the retention assembly may include arms and a cross-member joining the arms. The first CPA beam includes the CPA retention element, and the second CPA beam includes the retention assembly locking element. The arms include the locking contact surface, and the cross-member includes the CPA retention feature. Optionally, the retention assembly may include a retention member with first and second retention member surfaces. The first retention member surface includes the first retention feature. The second retention member surface includes the CPA retention feature.

[09] At least one embodiment of the present invention provides an electrical connector comprising a CPA, a plug housing, a header housing, a latch assembly, a latch retention assembly, and a CPA mounting assembly. The CPA includes a latch locking element and a CPA retention element. The plug housing has a body section with a mating interface on one end, and the header housing includes walls defining an opening to receive the mating interface.

[10] A latch assembly is mounted to the plug housing for maintaining the housings in contact when mated. The latch assembly includes a retention feature, a CPA retention feature, and a locking contact surface. The latch assembly is movable between latched and unlatched positions. A latch retention assembly is mounted to the header housing, and includes a latch retention surface. The latch retention surface cooperates with the retention feature to prevent the separation of the plug and header housings when they are mated and the latch is in the latched position.

[11] A CPA mounting assembly is mounted to the plug housing. The CPA is slidably mounted to the CPA mounting assembly and is movable to unmated and mated positions. In the unmated position, the CPA permits deflection of the latch assembly and engagement and disengagement of the plug and header housings. When the CPA is in the mated position, the latch locking element cooperates with the locking contact surface to prevent the latch assembly from moving to the unlatched position, thereby preventing engagement and disengagement of the plug and header housings. The CPA retention element cooperates with the CPA retention feature to maintain the CPA in the mated position.

[12] Optionally, the latch locking element may include a raised surface, and the latch assembly may include an interfering surface and a clearance surface. The interfering surface is substantially parallel to the raised surface when the latch assembly is in the latched position, and the interfering surface contacts the raised surface when the latch assembly is biased toward the unlatched position and the CPA is in the mated position. The clearance surface is sloped relative to the raised surface when the latch assembly is in the latched position, and does not contact the raised surface when the latch assembly is in the unlatched position and the CPA is in the unmated position.

[13] At least one embodiment of the present invention provides an electrical connector half assembly including a CPA and a connector housing. The CPA includes a retention assembly locking element and a CPA retention element. A retention assembly is mounted to the connector housing. The retention assembly includes a housing retention feature, a CPA retention feature, and a locking contact surface. The retention assembly is movable between locked and unlocked positions. A CPA mounting assembly is mounted to the connector housing, and the CPA is slidably mounted to the CPA mounting assembly and movable between first and second positions. The CPA permits biasing of the retention assembly when in the first position. The retention assembly locking element cooperates with the locking contact surface to prevent the retention assembly from moving to the unlocked position when the CPA is in the second position. The CPA retention element cooperates with the CPA retention feature to maintain the CPA in the second position.

[14] Certain embodiments of the present invention thus provide a CPA and connector housing for electrical connectors. The CPA, in addition to providing position assurance, allows a CPA to be used with a connector half not originally designed for use with a CPA. The CPA is prevented from inadvertently advancing to a position indicating the connector halves are mated when the connector halves are separated. The CPA is also secured in position when the connector halves are mated.

## BRIEF DESCRIPTION OF THE DRAWINGS

[15] Figure 1 illustrates an isometric view of a connector assembly with a CPA in the unmated position formed in accordance with an embodiment of the present invention.

[16] Figure 2 illustrates an isometric view of a connector assembly with a CPA in the mated position formed in accordance with an embodiment of the present invention.

[17] Figure 3 illustrates an isometric view of a header housing used in accordance with an embodiment of the present invention.

[18] Figure 4 illustrates a front isometric view of a plug housing formed in accordance with an embodiment of the present invention.

[19] Figure 5 illustrates a rear isometric view of a plug housing formed in accordance with an embodiment of the present invention.

[20] Figure 6 illustrates an isometric view of a CPA formed in accordance with an embodiment of the present invention.

[21] Figure 7 illustrates a sectional view taken along line 7-7 in Fig. 1 of a mated connector assembly with the CPA in the unmated position in accordance with an embodiment of the present invention.

[22] Figure 8 illustrates a sectional view taken along line 8-8 in Fig. 2 of a mated connector assembly with the CPA in the mated position in accordance with an embodiment of the present invention.

[23] The foregoing summary, as well as the following detailed description of the preferred embodiments of the present invention, will be better understood when read in conjunction with the appended drawings. For the purpose of illustrating the invention, there is shown in the drawings, embodiments which are presently preferred.

It should be understood, however, that the present invention is not limited to the precise arrangements and instrumentality shown in the attached drawings.

#### DETAILED DESCRIPTION OF THE INVENTION

[24] Figure 1 illustrates an isometric view of a connector assembly 20. The connector assembly 20 comprises a header housing 22, a plug housing 24, and a connector position assurance device (CPA) 26. In Fig. 1, the header housing 22 and plug housing 24 are shown mated, and the CPA 26 is in the unmated position. Figure 2 illustrates an isometric view of the connector assembly 20 with the header housing 22 and the plug housing 24 mated, and the CPA 26 in the mated position.

[25] Figure 3 illustrates an isometric view of the header housing 22. The header housing 22 includes a front end 30, a rear end 32, a top portion 34, a bottom portion 36, and walls 38. The walls 38 join the top portion 34 and the bottom portion 36 with an opening 40 being defined by the interior surfaces of the walls 38 at the front end 30 of the header housing 22. The opening 40 receives the mating interface of the plug housing 24. Towards the rear end 32 of the header housing 22, the opening 40 includes apertures 42 designed to hold pins (not shown) that meet contacts within the plug housing 24 when the header housing 22 and plug housing 24 are mated, providing electrical communication therebetween. A wire harness (not shown) may be connected to the header housing 22 proximal to the rear end 32. The illustrated header housing 22 is an existing model that was designed for use without a CPA.

[26] Further, the header housing 22 includes a latch retention bump 44. The latch retention bump 44 extends downward from the interior top surface of the top portion 34 of the header housing 22 proximal to the front end 30 and comprises a sloped surface 46, a flat surface 48, and a retention surface 50. The sloped surface 46 extends generally downward from the top portion 34 and back toward the rear end 32. The sloped surface 46 terminates at the flat surface 48 leading to the retention surface 50. The retention surface 50 extends downward generally perpendicularly from the top portion 34 and faces the rear end 32.

[27] Figures 4 and 5 illustrate isometric views of the plug housing 24. The plug housing 24 includes a front end 60, a rear end 62, a top portion 64, a bottom portion 66, and sides 68. The sides 68 join the top portion 64 and the bottom portion 66. The plug housing 24 includes a mating interface 70 proximal to the front end 60. The mating interface 70 includes receptacles 72 that correspond in alignment to the apertures 42 in the rear end 32 of the header housing 22, and hold contacts (not shown) that electrically connect with the pins of the header housing 22 when the header housing 22 and plug housing 24 are mated. A wire harness (not shown) may be mounted proximal to the rear end 62 of the plug housing 24.

[28] As shown in Fig. 5, the top portion 64 of the plug housing 22 includes side rails 73 that include slots 74 facing one another. The slots 74 begin proximal to the rear end 62 of the plug housing 22 and extend into the plug housing 22. The slots 74 include slot protrusions 76, slot sides 84, and shelves 86. The slot sides 84 are located proximal to the interior surface of the sides 68. The slot protrusions 76 extend from the slot sides 84 and each comprise a protrusion sloped surface 78, a protrusion flat surface 80, and a protrusion retaining surface 82. The protrusion sloped surface 78 extends generally away from the slot side 84 and toward the front end 60 of the plug housing 24. The protrusion sloped surface 78 terminates at the protrusion flat surface 80 extending substantially parallel to the slot side 84 and toward the front end 60 of the plug housing 24. The protrusion retaining surface 82 extends substantially perpendicularly away from the slot side 84 and meets the protrusion flat surface 80. The shelves 86 extend substantially perpendicularly from the bottom of the slot sides 84. The slot 74 is sized and configured to accept the CPA 26, and the slot protrusions 76 help maintain the CPA 26 inside the slot 74 after the CPA 26 is mounted in the slot 74.

[29] The plug housing 24 also includes a latch assembly 88. As shown in Fig. 4, the latch assembly 88 includes latch beams 90, a cross-member 100, and a latch finger rest 112. The latch assembly 88 cooperates with the latch retention bump 44 of the header housing 22 to maintain the header housing 22 and the plug housing 24 in contact after they are mated.

[30] The illustrated embodiment of the plug housing 24 includes two latch beams 90 located symmetrically about the central axis of the plug housing 24. The latch beams 90 each comprise a base 92 and an arm 94. The base 92 is located proximal to the front end 60 and the top portion 64. The arm 94 extends away from the base 92 to a latch beam free end 95 located toward the rear end 62 of the plug housing 24. The latch arms 94 may be deflected under an imposed force, the largest deflection being at the latch beam free end 95. Each arm 94 includes a bottom surface 96 and a bottom sloped surface 98. The bottom surface 96 is substantially parallel to the slot 74 (Fig. 5) (when the latch assembly 88 is unbiased) and located nearer to the top portion 64 than the top of the slot 74. Proximal to the latch beam free end 95, the bottom surface 96 terminates, meeting the bottom sloped surface 98. The bottom sloped surface 98 extends toward the latch beam free end 95 and toward the top portion 64 from the bottom surface 96.

[31] As shown in Fig. 4, the cross-member 100 joins the arms 94 at an intermediate position along the length of the arms 94. The cross-member 100 includes a first sloped surface 102, a second sloped surface 104, a top surface 106, a bottom surface 107, and a retention surface 108. The first sloped surface 102 slopes toward the top portion 66 and the rear end 62 of the plug housing 24, and is used to facilitate biasing of the latch assembly 88 during mating by cooperating with the sloped surface 46 of the latch retention bump 44. The second sloped surface 104 extends toward the bottom portion 66 and the rear end 62 from the point where the first sloped surface 102 and the second sloped surface 104 join. The second sloped surface 104 is used to help maintain the CPA 26 in the mated position. The top surface 104 extends toward the rear end 62 substantially parallel to the bottom surface 96 from the point where the top surface 104 meets the first sloped surface 102. Towards the latch beam free end 95, the retention surface 108 extends from the top surface 106 substantially perpendicular to the top surface 106. The opening 110 extends through the top surface 106 proximal to the retention surface 108. The retention surface 108 cooperates with the retention surface 50 of the latch retention bump 44 (Fig. 3) to maintain the header housing 22 and the plug housing 24 in contact. The bottom surface 107 joins the second sloped surface 104 and the retention surface 108, and is substantially parallel to the top surface 106.



[32] The latch finger rest 112 is mounted to the latch assembly 88 proximate to the latch beam free end 95. The latch finger rest 112 is used to manually bias the latch assembly 88 to the unlatched position to facilitate engagement and disengagement of the header housing 22 and the plug housing 24. Locating the latch finger rest 112 at the latch beam free end 95 provides the greatest mechanical advantage for deflecting the latch beams 90 about bases 92.

[33] Figure 6 illustrates an isometric view of the CPA 26. The CPA 26 includes a front end 120 and a back end 122. The CPA further includes a body 123, a center beam 124, side beams 134, and a CPA finger rest 154. The body 123 is located proximal to the back end 122 of the CPA 26. The center beam 124 extends from the body 123 to the center beam free end 127. Proximal to the center beam free end 127, the center beam 124 includes a CPA bump 126. The CPA bump includes a front surface 128, a top surface 130, and a back surface 132. The front surface 128 extends from the top surface of the center beam 124. The top surface 130 is joined to the front surface 128 and extends from the point where it joins the front surface 128 away from the center beam free end 127 substantially parallel to the top surface of the center beam 124. The back surface 132 extends from the top surface 130 towards the top surface of the center beam 124 and at a small angle away from the center beam free end 127.

[34] The side beams 134 extend from the body 123 on either side of the center beam 124 toward their side beam free ends 135. The side beams 134 each include a top surface 136, a side 137, a bottom surface 138, a leading surface 140, a side flat surface 142, a side retention surface 144, a necked-down portion 146, and a pad 149. The top surface 136 and the bottom surface 138 are substantially parallel to each other and joined by the side 137 on the exterior of the CPA 26. The side 137 and the side flat surface 142 are configured to be slidably accepted by the slot 74.

[35] The leading surface 140 of each side beam 134 begins proximate to the side beam free end 135, is substantially perpendicular to the top surface 136 and the bottom surface 138, and extends generally away from the side beam free end 135 and toward the outside of the CPA 26. The leading surface 140 ends at the side flat surface 142. The side flat surface 142 extends from the leading surface 140 away

from the side beam free end 135, and is substantially coplanar with the side 137. The side retention surface 144 extends substantially perpendicularly from the side flat surface 142 toward the inside of the CPA 26. The side retention surface 144 cooperates with the slot protrusion 76 to maintain the CPA 26 in the slot 74.

[36] The necked-down portion 146 extends from the side retention surface 144 away from the side beam free end 135. The necked-down portion 146 includes a necked-down side 147 and a necked-down sloped surface 148. The necked-down side 147 extends from the side retention surface 144 substantially parallel to the side until it terminates at the necked-down sloped surface 148. The necked-down sloped surface 148 extends from the necked-down side to join the side 137. The necked-down portion 146 is sized to provide clearance from the slot protrusion 76 when the CPA 26 is moved between the mated and unmated positions.

[37] Each pad 149 includes a pad top surface 150 and pad sides 152. The pad sides 152 extend substantially perpendicularly from the top surface 136 of the side beam 134 to a raised surface, the pad top surface 150. The pad top surface 150 is substantially parallel to the top surface 136 of the side beam 134. The pad 149 cooperates with the bottom surface 96 to prevent the latch assembly 88 from deflecting to the unlatched position when the CPA 26 is in the mated position, thereby maintaining contact between the header housing 22 and the plug housing 24.

[38] The CPA finger rest 154 is located proximal to the back end 122 of the CPA 26 and includes a back 156, sides 158, and a finger rest opening 160. The back 156 and sides 158 together define a "C"-shaped finger rest opening 160. The finger rest opening 160 is sized to accept the latch finger rest 112 when the CPA 26 is moved to the mated position. The CPA finger rest 154 is used by an operator to move the CPA 26 between the mated and unmated positions.

[39] The plug housing 24 includes features required for the use of the CPA 26, and the plug housing 24 and CPA 26 can be used with the existing header housing 22. This allows the connector assembly 20 to utilize a CPA 26 while including the header housing 22 which was originally designed without the CPA 26 in mind. Thus, the plug housing 24 and CPA 26 can be used to upgrade existing header housings to

accommodate the use of the CPA 26. This also allows for a single header design to be economically used in both CPA and non-CPA applications.

[40] Sliding the front end 120 of the CPA 26 into the slot 74 proximal to the rear end 62 of the plug housing 24 mounts the CPA 26 in the plug housing 24. The slot sides 84 slidably accept the sides 137 and the side flat surfaces 142 of the CPA 26. As the CPA 26 advances into the slot 74, the leading surface 140 of each side beam 134 encounters the protrusion sloped surface 78 of the slot protrusion 76. The bottom surfaces 138 of the side beams 134 rest on the shelves 86. Further advancement of the CPA 26 causes the leading surface 140 to slide against the protrusion sloped surface 78, thereby biasing the side beam free end 135 inward, away from the slot side 84. As the CPA 26 is still further advanced, the side flat surface 142 of the side beam 134 slides against the protrusion flat surface 80 until the side retention surface 144 is past the protrusion flat surface 80. At this point, the side beam 134 returns to its unbiased orientation, and, if removal of the CPA 26 is attempted, an interference between the side retention surface 144 of the side beam 134 and the protrusion retaining surface 82 prevents removal of the CPA 26 from the plug housing 24.

[41] With the CPA 26 located in the plug housing 24 with the side retention surface 144 just past the protrusion flat surface 80, the front surface 128 of the CPA bump 126 is located slightly more toward the rear end 62 of the plug housing 24 than the retention surface 108 of the cross member 100. This position is the unmated position. An interference between the front surface 128 and the retention surface 108 prevents further advancement of the CPA 26 toward the front end 60 of the plug housing 24 from the mated position. To further advance the CPA 26, the center beam free end 127 of the CPA 26 must be biased so that the front surface 128 can clear the retention surface 108. Thus, the CPA 26 is prevented from inadvertent movement from the unmated position, which would interfere with the mating of the header housing 22 and the plug housing 24.

[42] To mate the header housing 22 and the plug housing 24, the housings are oriented with their respective front ends 30, 60 facing each other, and the housings are then urged toward each other. As the housings are brought together, the mating interface 70 of the plug housing 24 is accepted by the opening 40 of the header

housing 22. As the mating interface 70 further enters the opening 40, the first sloped surface 102 of the cross member 100 will encounter the sloped surface 46 of the latch retention bump 44. As the first sloped surface 102 slides against the sloped surface 46, the latch assembly 88 will be biased from its substantially horizontal position as the latch beam free end 95 will be deflected toward the bottom portion 66 of the plug housing 24.

[43] Further urging together of the housings will result in the first sloped surface 102 sliding past the sloped surface 46, and the top surface 106 of the cross-member 100 will contact and slide along the flat surface 48 of the latch retention bump 44. When the latch assembly 88 is biased such that the top surface 106 is as near or nearer to the bottom portion 66 as the flat surface 48 is, the header housing 22 and plug housing 24 may be engaged and disengaged. This is known as the unlatched, or unlocked, position.

[44] Once the top surface 106 has passed the flat surface 48, the latch assembly 88 will return to its original position, and the latch beam 90 will no longer be deflected. This is referred to as the latched, or locked position. With the cross-member 100 now nearer the rear end 32 of the header housing 22 than the latch retention bump 44 is and the latch assembly 88 in the latched position, the retention surface 108 of the cross-member 100 and the retention surface 50 of the latch retention bump 44 now face each other and cooperate to form an interference preventing separation of the header housing 22 and the plug housing 24.

[45] Simultaneous to the unbiasing of the latch assembly 88 as the top surface 106 and flat surface 48 pass each other, the flat surface 48 of the latch retention bump will contact the top surface 130 of the CPA bump 126. This contact will bias the center beam 124 of the CPA 26 by deflecting the center beam free end 127 down toward the bottom portion 66. The latch retention bump 44, cross-member 100, and CPA bump 126 are configured to allow this deflection to bias the center beam 124 such that the front surface 128 can clear the retention surface 108 and the CPA 26 can be moved from the unmated position.

[46] Figure 7 illustrates a sectional view taken along line 7-7 of Fig. 1, and shows the header housing 22 mated to the plug housing 24 with the CPA 26 in the unmated

position. In Fig. 7, the interference between the latch retention bump 44 and the CPA bump 126 is illustrated; in practice, the center beam free end 127 would be deflected downward toward the bottom portion 66, and the top surface 130 of the CPA bump 126 would be contacting the flat surface 48 of the latch retention bump 44. Thus, as indicated above, the CPA 26 may be advanced toward the rear end 32 of the header housing 22 and into the mated position.

[47] With the CPA 26 in the unmated position as shown in Fig. 7, only the bottom sloped surface 98, and not the bottom surface 96 of the latch beam 90 are immediately above the pad 149. A downward force may be exerted on the latch finger rest 112 to bias the latch assembly 88. As the latch beam 90 is deflected downward, the bottom sloped surface 98 will approach the pad top surface 150, but the latch assembly 88 will enter the unlatched position before the bottom sloped surface 98 and the pad top surface 150 make contact. Thus, the housings may be unmated with the CPA 26 in the unmated position. Further, the pad 149 and bottom sloped surface 98 may be sized so that they contact soon after the latch assembly 88 is past the unlatched position, thereby minimizing any excess, unnecessary deflection of the latch assembly 88 that could result in damage or breakage. To advance the CPA 26 to the mated position, an operator exerts a force on the CPA finger rest 154 urging the CPA toward the rear end 32 of the header housing 22 (put another way, toward the front end 60 of the plug housing 24). As the CPA 26 advances from the unmated position, the top surface 130 of the CPA bump 126 will slide past the flat surface 48 of the latch retention bump 44, and then across the bottom surface 107 of the cross-member 100. Once the CPA 26 has advanced such that the top surface 130 has slid past the bottom surface 107, the center beam 124 will return to its unbiased position, and the CPA 26 will be in the mated position.

[48] Figure 8 illustrates a sectional view taken along line 8-8 of Fig. 2, and shows the header housing 22 mated to the plug housing 24 with the CPA 26 advanced to the mated position. With the CPA 26 in the mated position, a portion of the bottom surface 96 of the latch beam 90 is directly above a portion of the pad top surface 150. Thus, if the a downward force is applied to the latch finger rest 112, the bottom surface 96 will approach the pad top surface 150. The bottom surface 96 will contact

the pad top surface 150 before the latch assembly 88 has reached the unlatched position. Because the shelves 86 (Fig. 5) support the CPA 26, the contact between the bottom surface 96 and the pad top surface 150 will prevent further biasing of the latch assembly 88. Thus, with the CPA 26 in the mated position, the latch assembly 88 cannot be moved to the unlatched position, and the housings will be maintained in contact. When the CPA 26 is in the mated position, the CPA finger rest opening 160 has advanced to partially surround the latch finger rest 112, making accessing the latch finger rest 112 via a finger or thumb more difficult. Thus, the CPA 26 provides a visual and tactile cue that the housings are mated and the latch assembly 88 cannot be moved to the unlatched position.

[49] If an attempt is made to move the CPA 26 from the mated position of Fig. 8 to the unmated position, the back surface 132 of the CPA bump 126 will encounter the second sloped surface 104 of the cross-member 100. The resulting interference will resist the movement toward the unmated position. This resistance prevents inadvertent movement of the CPA 26 from the mated to the unmated position. The back surface 132 and second sloped surface 104 are configured, however, to provide a slight leading angle such that they may slide against each other if an intentional force is applied by an operator to the CPA finger rest 154, and the CPA 26 may be moved to the unmated position prior to unmating of the housings.

[50] To separate the housings, the CPA 26 is moved to the unmated position, and a downward force is applied to the latch finger rest 112, biasing the latch assembly 88 to the unlatched position. With the CPA 26 in the unmated position and the latch assembly 88 in the unlatched position, the header housing 22 and the plug housing 24 may now be separated.

[51] While particular elements, embodiments and applications of the present invention have been shown and described, it will be understood, of course, that the invention is not limited thereto since modifications may be made by those skilled in the art, particularly in light of the foregoing teachings. For example, the plug and header housings could be reversed, with, for example, the CPA mounted to the header housing. It is therefore contemplated by the appended claims to cover such

modifications as incorporate those features which come within the spirit and scope of the invention.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231  
223